

## Asymmerical TVS Diode for Extended Common-Mode RS-485

### PROTECTION PRODUCTS

### **Description**

The SM712 transient voltage suppressor (TVS) diode is designed for asymmetrical (12V to -7V) protection in multi-point data transmission standard RS-485 applications. The SM712 may be used to protect devices from transient voltages resulting from electrostatic discharge (ESD), eletrical fast transients (EFT), and lightning.

The SM712 features more than 500 Watts (tp = 8/20 µs) of power handling capability to accommodate the higher transient voltage levels which may be expected in extended commom mode applications. This provides higher equipment reliability and eliminates the "guess work" required when using Zener diodes that are not rated to handle such transient conditions.

The SM712 replaces four discrete components by integrating two 12V and two 7V TVS diodes in a single package. The integrated design aids in reducing voltage over-shoot associated with trace inductance. The low clamping voltage of SM712 minimizes the stress on the protected transceiver.

#### **Features**

- Transient Protection to
  - IEC 61000-4-2 (ESD): ±30kV (Air), ±30kV (Contact)
  - IEC 61000-4-4 (EFT): 40A (5/50ns)
  - IEC 61000-4-5 (Lightning): 21A for 12V TVS & 38A for 7V TVS (tp = 8/20μs)
- Protects two +12V to -7V lines
- Peak pulse power (tp = 8/20µs): 500-700W
- Low capacitance
- Low clamping voltage
- Solid-State Silicon-Avalanche Technology


### **Mechanical Characteristics**

- JEDEC SOT23 Package
- Molding Compound Flammability Rating: UL 94V-0
- Pb-Free, Halogen Free, RoHS/WEEE compliant
- · Marking: 712
- · Packaging: Tape and Reel


### **Applications**

- RS-485 tranceivers with extended common mode range
- Security systems
- Automatic Teller Machines
- HFC systems
- Networks

### **Circuit Diagram**



### **Schematic and Pin Configuration**



# **Absolute Maximum Ratings**

Rating	Symbol	Value	Units	
Peak Pulse Power (tp = $8/20\mu s$ )	P <sub>PK</sub>	550- 700	W	
Peak Pulse Current (tp = 8/20µs), Pin 1 or 2 to Pin 3		21	^	
Peak Pulse Current (tp = $8/20\mu s$ ), Pin 3 to Pin 1 or 2	I <sub>PP</sub>	38	Α	
ESD per IEC 61000-4-2 (Contact) <sup>(1)</sup>	V <sub>ESD</sub>	30	kV	
ESD per IEC 61000-4-2 (Air) <sup>(1)</sup>	ESD	30		
Lead Soldering Temperature	T <sub>L</sub>	260 (10 sec.)	°C	
Operating Temperature	T,	-55 to +125	°C	
Storage Temperature	T <sub>STG</sub>	-55 to +150	°C	

# **Electrical Characteristics (T=25°C unless otherwise specified)**

Parameter	Symbol	Conditions		Min.	Тур.	Max.	Units
Reverse Stand-Off Voltage	V <sub>RWM</sub>	Pin 1 or Pin 2 to 3				12	V
		Pin 3 to Pin 1 or 2				7	
Reverse Breakdown Voltage	$V_{\mathtt{BR}}$	I <sub>t</sub> = 1mA, Pin 1 or 2 to Pin 3		13.3			V
		I <sub>t</sub> = 1mA, Pin 3 and Pin 1 or 2		7.5			
Reverse Leakage Current	I <sub>R</sub>	V <sub>R</sub> = 12 V, Pin 1 or Pin 2 to 3				1	μΑ
		V <sub>R</sub> = 7 V, Pin 3 to Pin 1 or 2				20	
Clamping Voltage	V <sub>c</sub>	I <sub>pp</sub> = 5A, Pin 1 or 2 to Pin 3, tp = 8/20μs				20	V
		$I_{pp} = 5A$ , Pin 3 to Pin 1 or 2, tp = 8/20µs				10	V
Clamping Voltage	\/	I <sub>pp</sub> = 21A, Pin 1 or 2 to Pin 3, tp = 8/20μs				26	V
	V <sub>C</sub>	$I_{pp} = 38A$ , Pin 3 to Pin 1 or 2, tp = 8/20µs				19	V
Junction Capacitance	C,	V <sub>R</sub> = 0V	Pin 1 or 2 to Pin 3			75	
			Pin 3 to Pin 1 or 2			75	
		V <sub>R</sub> =12V	Pin 1 or 2 to Pin 3		57		pF
		V <sub>R</sub> =7V	Pin 3 to Pin 1 or 2		35		

#### Notes:


<sup>(1):</sup> ESD Gun return path to Ground Reference Plane (GRP)

<sup>(2):</sup> Transmission Line Pulse Test (TLP) Settings: tp = 100ns, tr = 0.2ns,  $I_{TLP}$  and  $V_{TLP}$  averaging window:  $t_1 = 70$ ns to  $t_2 = 90$ ns.


<sup>(3):</sup> Dynamic resistance calculated from  $I_{TLP} = 4A$  to  $I_{TLP} = 16A$ .

# **Typical Characteristics**


#### Non-Repetitive Peak Pulse Power vs. Pulse Time




#### **Power Derating Curve**




Clamping Voltage vs. Peak Pulse Current (tp =  $8/20\mu s$ )




Capacitance vs. Reverse Voltage



TLP IV Curve (Pin 1 or 2 to Pin 3)




TLP IV Curve (Pin 3 to Pin 1 or 2)




# **Typical Characteristics**

### ESD Clamping Voltage (+8kV Contact per IEC 61000-4-2)



### **ESD Clamping Voltage (-8kV Contact per IEC 61000-4-2)**



### **Application Information**

# **Device Connection for Protection of Two RS-485 Data Lines**

EIA RS-485 specifies a  $\pm$ 7V ground difference between devices on the bus. This permits the bus voltage to range from  $\pm$ 12V (5V  $\pm$  7V) to  $\pm$ 7V (0-7V).

The SM712 is designed to protect two RS-485 data lines in extended common mode applications. The SM712 may be used to protect devices from transient voltages resulting from ESD, EFT, and lightning. The device is designed with asymmetrical operating voltages for optimum protection. The TVS diodes at pins 1 and 2 have a working voltage of 12 volts. These pins are connected to the differential data line pairs. The TVS diodes at pin 3 have a working voltage of 7 volts. Pin 3 is connected to ground. The internal TVS diodes of the SM712 will protect the transceiver input from positive transient votlage spikes greater than 12V and negative spikes greater than 7V.


A series current limiting resistor may be added in applications requiring enhanced surge immunity.

#### **Circuit Board Layout Recommendations**


Good circuit board layout is critical for the suppression of fast rise time transients such as ESD. The following guidelines are recommended:

- Place the SM712 near the input terminals or connectors to restrict electromagnetic coupling.
- Minimize the path length between the SM712 and the protected line. This minimizes voltage overshoot due to parastic inductance of board traces.
- Use ground planes whenever possible.
- Long, single trace ground conductors should be avoided. The ground pin (Pin 3) should be connected directly to a ground plane on the circuit board for best results.
- Minimize all conductive loops including power and ground loops.
- Never run critical signals near board edges.


#### **RS-485 Common Mode Voltages**




#### **RS-485 Protection Circuit**




# **Outline Drawing - SOT-23**




## **Land Pattern - SOT-23**



# **Marking Code**



# **Tape and Reel Specification**



# **Ordering Information**

Part Number	<b>Qty per Reel</b>	Reel Size	Carrier Tape	Pitch			
SM712.TCT	3,000	7 Inch	Plastic	4mm			
MicroClamp and uClamp are registered trademarks of Semtech Corporation.							



#### **IMPORTANT NOTICE**

Information relating to this product and the application or design described herein is believed to be reliable, however such information is provided as a guide only and Semtech assumes no liability for any errors in this document, or for the application or design described herein. Semtech reserves the right to make changes to the product or this document at any time without notice. Buyers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. Semtech warrants performance of its products to the specifications applicable at the time of sale, and all sales are made in accordance with Semtech's standard terms and conditions of sale.

SEMTECH PRODUCTS ARE NOT DESIGNED, INTENDED, AUTHORIZED OR WARRANTED TO BE SUITABLE FOR USE IN LIFE-SUPPORT APPLICATIONS, DEVICES OR SYSTEMS, OR IN NUCLEAR APPLICATIONS IN WHICH THE FAILURE COULD BE REASONABLY EXPECTED TO RESULT IN PERSONAL INJURY, LOSS OF LIFE OR SEVERE PROPERTY OR ENVIRONMENTAL DAMAGE. INCLUSION OF SEMTECH PRODUCTS IN SUCH APPLICATIONS IS UNDERSTOOD TO BE UNDERTAKEN SOLELY AT THE CUSTOMER'S OWN RISK. Should a customer purchase or use Semtech products for any such unauthorized application, the customer shall indemnify and hold Semtech and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs damages and attorney fees which could arise.

The Semtech name and logo are registered trademarks of the Semtech Corporation. All other trademarks and trade names mentioned may be marks and names of Semtech or their respective companies. Semtech reserves the right to make changes to, or discontinue any products described in this document without further notice. Semtech makes no warranty, representation or guarantee, express or implied, regarding the suitability of its products for any particular purpose. All rights reserved.

© Semtech 2015

#### **Contact Information**

Semtech Corporation 200 Flynn Road, Camarillo, CA 93012 Phone: (805) 498-2111, Fax: (805) 498-3804 www.semtech.com